

Salient Features

- § Each of following independent Applied PE trainer may need a few set of associated panels (4 nos. typically) which are mounted in a light weight sturdy aluminum flat demo panel system.
- § Facilitates easy and safe wiring by students due to 4mm sturdy shrouded banana patch cords and shrouded socket arrangement for high voltage circuits.
- § Each panel has ABS molded plastic sturdy enclosure, and colorful screwless overlays showing circuit diagram & its connection tag numbers for easy understanding and connections.
- § Set of Instructor Guide & Student Workbook.



Mechanical specifications:

- **Aluminum rack:** of 1* 4 matrix used as flat panel demo panel system to house 4 panels needed for the trainer ordered.
- **Dimensions :** 500(H)*910(L)*300(D)mm

1] 3 Phase HV Thyristor control Trainer

Electrical Specifications

- Sturdy stud type 6 SCRs (anode to body type) with PIV rating 1000V/25Amp and 6 diodes with PIV ratings of 1000V/16A, however actual use is limited to 300W for equipment safety.
- 6 Nos. of Snubbers for protection of thyristors consisting of capacitor 0.1uF/1000V and 0.1E/5W ceramic resistors.
- The Power Module with 36 shrouded bananas to construct 3 phase HV circuit configurations.
- Cosine firing scheme to facilitate linear control between firing angle & DC load voltage, also gives better harmonic ripple control.

Panels needed

Input 3 phase DOL/MCB Starter panel (EMT1)

Integrated 3 phase AC measurement panel (EMT20).

3 phase SCR firing/Synchronizing Panel(PE4A)+ 6 SCR/Diode Power Module(PE4B)

Lamp load panel (EMT7) 100W x 3nos.

EMT6B : Voltmeter(600V), Ammeter(5A)

Inductive Load panel (EMT15A) (Optional).

Optionally 3 ϕ step down (430/110Vac) Isolation Transformer or 3 ϕ dimmer of 500VA may be ordered from safety point of view.

Optional 3 phase induction motor (F.H.P.).

Experiments covered

- Study of 3 phase SCR cosine firing circuits
- 3 Phase half bridge uncontrolled
- Full bridge uncontrolled
- Half bridge controlled
- Full bridge controlled
- Single phase cycloconverter (25Hz / 12.5Hz).
- 3 phase AC power control for resistive lamp load / 3 ϕ Induction motor (Optional).

2] Single phase dual converter trainer

Electrical specifications

- 2 No. CTs (1A/ 30mA)to detect current zero condition in each converter bridge
- 2 No. current limiting chokes with rating 750mH/1A
- 15W/60W lamp loads / DC motor 200Vdc/200W with1500rpm.
- 4 SCR based full bridge output 0V-195V / 3 Amp, cosine firing with linear characteristics

Panels Needed

Instrumentation power supply panel (EMT8).

2 Nos. of SCR actuator panels as Forward & Reverse controlled converter (EMT9 * 2 nos.)

Single phase dual converter controller panel (PE5).

1phase MCB isolator panel (EMT16).

Experiments covered

- Study of Dual converter topology & control strategy.
- Study of Dual converter operation : Resistive load / motor load.

3] Motor speed control trainer

Motor	DC Full wave converter	AC Controller
Method	PMDC 200V/200W motor Optional: i) 160W/180V shunt motor OR ii) 300W/180V DC motor with series shunt & compound winding	Fractional HP Universal AC/DC motor 230V AC / 1/12HP
Mechanical	Chassis mounted table top with brake pulley and spring balance (5kg).	
Speed feed back	Electronic : Tacho 0.5V/1000RPM, Optionally 10V/1000RPM electrical tacho only if PMDC motor ordered.	Electronic tacho 0.5V/1000RPM
Panels	<ul style="list-style-type: none"> • EMT8 : Instrumentation power supply. • EMT9 : Variable thyristor controlled power for Armature supply, One more EMT9 needed only if DC shunt motor ordered as field supply. • EMT6B : Voltmeter (300V), Ammeter (6A), Optional additional DC voltmeter with FF relay if DC shunt motor ordered. 	<ul style="list-style-type: none"> • EMT8 : Instrumentation power supply. • EMT9 : Variable thyristor controlled power for Armature supply. • EMT6 : Voltmeter (300V), Ammeter (1A).
Experiments	<ul style="list-style-type: none"> • Open loop torque speed characteristics. • Closed loop speed control using Armature voltage / speed feed back using P/PI mode 	<ul style="list-style-type: none"> • Open loop torque speed characteristics. • Closed loop speed control using speed feed back with AC controller using P/PI mode.

4] UPS Trainer (OFF line)

Electrical Specification

- ☐ Input Range is 170 – 270V A.C. / 50Hz.
- ☐ Output (Input present) 195 – 250V sine.
- ☐ Output (Input unhealthy/ absent) 230 +/- 5% Quasi-sine.
- ☐ Capacity 200W lamp load on AVR.
- ☐ Battery 12V / 7Ah, 'Panasonic' (maintenance free lead acid).
- ☐ Backup of 5 mins on 200W lamp load or 20 min. on one PC with colour monitor (14").
- ☐ Test points provided are 17

Panels needed

- Input / Output Module / UP1.
- Battery / Transformer Module / UP2.
- AVR / Charger Module / UP3.
- Inverter Module / UP4.

Experiments covered:

- Study of charger
- Study of Inverter
- Study of UPS

ANSHUMAN Tech Pvt. Ltd.

Plot 13, Sthairya, Behind Tol Hospital
Near Nav-Sahyadri Society, Karve Nagar
Pune – 411 052 (MH)INDIA

Tel : (0091)(020)25460892 / 25463052
Fax : (020) 25463052
Email : anshumanelectronics@vsnl.com /
info@anshumantech.com

Visit us at : www.anshue.com / www.anshumantech.com

Specifications subject to change without notice.

070801